



## XCFR2.E150931 Terminal Blocks - Component

[Page Bottom](#)

### Terminal Blocks - Component

[See General Information for Terminal Blocks - Component](#)**STELVIO SPA**

E150931


VIA AL MOGNAGO 49  
23848 OGGIONO, LC ITALY

Cat. No.	Wire Range	Wire Type	FW	TQ Lb In.	V	A	UG	CA
CMM, CZZ(1)	14-24	CU	2	5.0	300	16	B,C,D	2(105),*
CCC(2)	24-12	CU	2	5.0	300	14	B,C,D	2(105),*
CEE(2)	24-14	CU	2	5.0	300	14	B,C,D	2(105),*
COB(2)	24-12	CU	2	4.0	300	16	B,C,D	2(105),*
CBL(6)	30-12	CU	2	5.0	300	18	B,C,D	2(105)
MRT12(7)	30-14	CU	2	4.0	300	16	B,C,D	2(105),4,*
CUF(2)	24-12	CU	2	4.0	300	14	B,C,D	2(105),*
CUM(2)	N/A	CU	1	N/A	300	14	B,C,D	2(105),*
CUU(2)	24-12	CU	2	4.0	300	16	B,C,D	2(105),*
CZI(2)	26-14	CU	2	4.0	300	14	B,C,D	2(105)
CZM(2)	26-14	CU	2	4.0	300	14	B,C,D	2(105),*
<b>Note:</b> (1) - Followed by 5 or 10, followed by a one or two digit number, may be followed by suffix SQ, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (2) - Followed by 5, 5.08, 7.5, 10 or 10.16 followed by one or two digit number, may be followed by SQ, may be followed by A or B, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (6) - Followed by 5 or 10, followed by a one or two digit number, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (7) - followed by 5, 7.5 or 10, followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, BI, NA, MA or AR, may be followed by N0 up to N99.								
CPP(3)	30-16	CU	2	1.5	300	10	B,C,D	2(105),4*
CPA(3)	30-16	CU	2	2.5	300	10	B,C,D	2(105),4*
<b>Note:</b> (3) Followed by 3.5, 3.81, 5, 5.08, 7, 7.5, 7.62, 10 or 10.16 followed by one or two digit number, may be followed by A or B, may be followed by SQ or SELV, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
CLL(4)	30-12	CU	2	4	300	14	B,C,D	2(105),4*
CIA(4)	30-14	CU	2	4	300	14	B,C,D	2(105),*
CII(4)	30-14	CU	2	4	300	14	B,C,D	2(105),*
CKK(4)	30-12	CU	2	5	300	16	B,C,D	2(105),*
CTL(4)	(6)	CU	2	N/A	300	10	B,C,D	2(105),*
CLA(4)	30-12	CU	2	4	300	14	B,C,D	2(105),4*
<b>Note:</b> (4) Followed by 5, 5.08, 7.5, 7.62, 10 or 10.16 followed by one or two digit number, with or without A or B, may be followed by suffix SQ, SELV, LC or SQLC, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (6) Wire range Nos. 16sol/STR AWG , 18AWG Sol or No. 22 Sol AWG wire only.								

MRT1(1)	16-30	CU	2	N/A	300	10	B,D	1,2(105)
MRT13 (2)	16-30	CU	2	N/A	300	8	B,D	2(105)
MRT24 (3)	16-30	CU	2	N/A	300	4	B,D	2(105)
MRT23 (4)	16-30	CU	2	N/A	300	10	B,D	2(105)
<b>Note:</b> (1) Followed by P5, P5.08, P7.5, P7.62, P10, P10.16, followed by a one or two digit number, may be followed by V01 up to V99, followed by BL, GR, GR1, NE, RO, VE, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (2) Followed by P3.5, P3.81, P7, P7.62 followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, VE, NE, RO, BL, AR, NA, BI, MA or GR1, may be followed by N0 up to N99.								
<b>Note:</b> (3) Followed by P3.5, P3.81, P7, P7.62 followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, VE, NE, RO, BL, AR, NA, BI, MA or GR1, may be followed by N0 up to N99.								
<b>Note:</b> (4) Followed by P5.08, P10.16, followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, VE, NE, RO, BL, AR, NA, BI, MA or GR1, may be followed by N0 up to N99.								
CPF(2)	12-24	CU	2	5.0	300	12	B,D	2(105)
CPM(3)	N/A	CU	1	N/A	300	12	B,D	2(105)
MRT3(1)	12-30	CU	2	5.0	300	12	B,D	2(105)
MRT21(4)	N/A	CU	1	N/A	300	12	B, C, D	2(105)
MRT8(5)	30-16	CU	2	3.0	300	8	B,D	2(105)
MRT9(6)	N/A	CU	1	N/A	300	8	B,D	2(105)
MRT22(7)	30-16	CU	2	2.0	300	8	B,D	2(105)
CHM(8)	N/A	CU	2	N/A	300	6	B,D	2(105)
CHF(9)	30-16	CU	2	3.0	300	6	B,D	2(105)
<b>Note:</b> (1) Followed by P5, P5.08, P10 or P10.16, followed by a one or two digit number, may be followed by LC, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (2) Followed by 5, 5.08, 7.5, 7.62, 10, 10.16 followed by a one or two digit number, may be followed by LC, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (3) Followed by 5, 5.08, 7.5, 7.62, 10, 10.16 followed by a one or two digit number, may be followed by an A or SQ, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (4) Followed by P5, P5.08, P10 or P10.16, followed by one or two digit number, may be followed by V01 up to V99, may be followed by SQ, may be followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (5) - Followed by P3.5, P3.81, P7, P7.62, followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (6) Followed by P3.5, P3.81, P7, P7.62, followed by a one or two digit number, may be followed by SQ, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (7) Followed by P3.81, P7.62, followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (8) Followed by 5 or 10, followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (9) Followed followed by 5 or 10, followed by one or two digit number, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
MRT4(1)	12-30	CU	2	5.0	300	16	B, C, D	2(105)
MRT5(2)	12-30	CU	2	5.0	300	16	B, C, D	2(105)
MRT6(3)	12-30	CU	2	5.0	300	16	B, C, D	2(105)
MRT15(4)	12-30	CU	2	5.0	300	16	B, C, D	2(105), 4
MRT18(5)	12-30	CU	2	5.0	300	16	B, C, D	2(105), 4
MRT19(6)	30-10	CU	2	5.0	300	22	B, D	2(105), 4
MRT20(7)	10-30	CU	2	5.0	300	24	B, C, D	2(105)
<b>Note:</b> (1) Followed by P5 or P10, followed by a one or two digit number, may be followed by SQ, may be followed by V01 up to V99, followed by GR, NE, GR1, RO, BL, AR, NA, BI, MA or VE, may be followed by N0 up to N99.								
<b>Note:</b> (2) Followed by P5, P5.08, P7.5, P7.62, P10 or P10.16, followed by a one or two digit number, may be followed by SQ, DP, may be followed by V01 up to V99, followed by GR, NE, GR1, RO, BL, AR, NA, BI, MA or VE, may be followed by N0 up to N99.								

<b>Note:</b> (3) Followed by P5 or P10, followed by a one or two digit number, may be followed by V01 up to V99, followed by GR, NE, GR1, RO, BL, AR, NA, BI, MA or VE, may be followed by N0 up to N99.								
<b>Note:</b> (4) Followed by P5, P5.08, P10 or P10.16 followed by a one or two digit number, may be followed by SQ or DP, may be followed by V01 up to V99, followed by AR, GR, VE, GR1, RO, BL, NA, BI, MA or NE, may be followed by N0 up to N99.								
<b>Note:</b> (5) Followed by P5.08 or P10.16 followed by one or two digit number, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (6) Followed by P8, followed by /2, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (7) Followed by P6.35 or P9.52 followed by one or two digit number, may be followed by V01 up to V99, may be followed by GR, GR1, VE, NE, BL, RO, AR, NA, BI or MA, may be followed by N0 up to N99.								
CQQ, CQS (1)	N/A	CU	1	N/A	300	6	B, C, D	2(80)
CQQ, CQS (2)	N/A	CU	1	N/A	300	10	B, C, D	2(80)
CQQ, CQS (3)	N/A	CU	1	N/A	300	16	B, C, D	2(80)
<b>Note:</b> (1) Followed by A, B, C, D, E or F, followed by a one or two digit number, followed by 2.8, may be followed by OT, may be followed by V01 up to V99, followed by GR, NE, GR1, VE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (2) Followed by A, B, C, D, E or F, followed by a one or two digit number, followed by 5, may be followed by OT, may be followed by V01 up to V99, followed by GR, NE, GR1, VE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
<b>Note:</b> (3) Followed by A, B, C, D, E or F, followed by a one or two digit number, followed by 6.3 or 2863, may be followed by OT, may be followed by V01 up to V99, followed by GR, NE, GR1, VE, RO, BL, AR, NA, BI or MA, may be followed by N0 up to N99.								
MRT26(1)	6-20	CU	2	12	300	40	B, C, D	2(105), 4
MRT27(2)	6-20	CU	2	12	300	40	B, C, D	2(105), 4
<b>Note:</b> (1) Followed by P10.16, followed by one or two digit number, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, NA, BI, MA or AR, may be followed by N0 up to N99.								
<b>Note:</b> (2) Followed by P10.16, followed by one or two digit number, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, NA, BI, MA or AR, may be followed by N0 up to N99.								
MRT33(1)	N/A	CU	1	N/A	300	8	B, C, D	2(105)
<b>Note:</b> (1) Followed by P3.81 or P7.62, followed by one or two digit number, may be followed by SQ, may be followed by V01 up to V99, followed by GR, GR1, VE, NE, BL, RO, NA, BI, MA or AR, may be followed by N0 up to N99.								



Marking: Company name or trademarks **CHIRI** or  and catalog designation (catalog designation may appear on shipping carton).

Last Updated on 2008-03-27

[Questions?](#)

[Notice of Disclaimer](#)

[Page Top](#)

Copyright © 2008 Underwriters Laboratories Inc.®

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Listed and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Designs and/or Listings (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from Underwriters Laboratories Inc." must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "Copyright © 2008 Underwriters Laboratories Inc.®"

An independent organization working for a safer world with integrity, precision and knowledge.

