

# Phase Rotation Indicators

Checks phase sequence and phase status

## Features:

- 100-660 VAC rated test range for testing phase orientation of three phase power sources over 50-70 Hz frequency range
- Five LEDs: two of which indicate phase orientation (clockwise or counter-clockwise); and whether each of three phases is live
- Simple operation
- Complete with three large alligator clips
- Weight 5oz. (140g)
- Dimensions: 3.5x2x1" (90x50x25mm)

## Motor Rotation & 3-Phase Tester

- Combines above 3-phase rotation tester with a motor rotation tester for measuring the rotation direction of motor shafts
- Ensures motor is not damaged from incorrect wiring
- Complete with three large alligator clips
- Weight 10oz. (283g)
- Dimensions: 5.9x3.3x1.5" 150x84x38mm)



CE

## Ordering Information:

480300 .....Phase Rotation Tester

480303 .....Motor Rotation &amp; 3-Phase Tester

## Accessories

409996 .....Vinyl Pouch Carrying Case